

13 Wall & Ceiling LED>The Backlight Cylinders

12120A/W/W



18W Downlight + 2W Uplight COB LED Cylinder. Gun Black Reflector.

Complete with non-dimmable LED driver.


Complies with standard EN60598-1 and any other specific standards.



Downloads





Dimensions



Physical Specification

| | |
|-----------------|-------------------------|
| Item Group | 13 Wall & Ceiling LED |
| Family | The Backlight Cylinders |
| Order Code | 12120A/W/W |
| Colour | White |
| Material | Aluminium |
| Shape | Circular |
| Height | 116mm |
| Diameter | 100mm |
| Surface Ceiling | Yes |
| Indoor | Yes |
| Adjustable | No |

| Gear | | Built In | |
|------------------|--|---|--|
| Fitting + Driver | | | |
| Input Voltage | | 220-240V | |
| 50 Hz | | Yes | |
| 60 Hz | | Yes | |
| Safety Class | |  | |
| Power(Watts) | | 18W+2W | |
| IP Rating | | IP20 | |
| Light Source | | LED built in | |
| Dimmable | | No | |
| F Mark | |  | |

| Fitting | | | |
|---------------|--|------------------|--|
| Input Type | | Constant Current | |
| Input Current | | 500mA | |
| IP Rating | | IP20 | |
| Light Source | | LED built in | |
| LED Type | | COB | |
| LED Brand | | Cree | |

| Gear | | | |
|------------------|--|------------|--|
| Gear Type | | Led Driver | |
| Input Voltage | | 220-240V | |
| 50 Hz | | Yes | |
| 60 Hz | | Yes | |
| Power(Watts) | | 14-21,5W | |
| Constant Current | | Yes | |
| 500mA | | 28-43V | |
| IP Rating | | IP20 | |

| |
|------------------|
| Safety Class |
| Dimmable |
| Housing Material |



No

Plastic

Illumination Data

| | |
|----------------------|--|
| Colour Temperature | 3000K |
| Lumen Output | 1800lm |
| Light Efficiency | 90lm/W |
| CRI | 90 |
| Beam Angle | 60° |
| Illumination Diagram |  |
| Dark Light | Yes |

Packing Info

| | |
|------------|---------------|
| Pcs/Carton | 30 |
| Barcode | 5291889079576 |
| HS Code | 9405413990 |

Certification & Warranty

| | |
|----------------|---------|
| Warranty | 3 years |
| Weee Directive | Yes |

switch to
one light!

one
LIGHT

